



Safety Communicator

Personal information and communication hub

Safety Communicator

Safety Communicator is an industrial-grade smartphone and app serving as a personal information and communication hub for industrial workers.

Part of ConneXt Safety Solutions, Safety Communicator takes the Bluetooth® signal from a personal safety device and relays its data in real time to a remote host controller. It enables constant visibility of your workers' safety, so you can make fast, informed decisions to protect your workers, prevent a crisis and optimize operations.

With Bluetooth Low Energy (BLE) technology, the Safety Communicator is a great way to get wireless connectivity – without the expense of a private network. And if you already have a Wi-Fi or mesh network, Safety Communicator helps ensure continuous wireless monitoring when a worker is out of range.

Simply pair your safety device with the intrinsically safe, ruggedized, glove-friendly smartphone. Then use the Safety Communicator smartphone app to send data from the device using a publicly available cellular network to the real-time monitoring software in a remote location.



Enhanced Safety

- Real-time monitoring
- Location tracking
- Instrument association
- Personal profile and settings

Better Productivity

- Performance support
- Subject matter expert access
- Automatic data collection

Improved Compliance

- Reports
- Policy Enforcement

Ultra Ruggedized Smartphone

- Global approval for worldwide acceptance
 - IP-68 water- and dust-resistant
 - Short- and Long-range Communication
 - NFC
 - BLE
 - Wi-Fi
 - LTE (3G, 4G)
 - 8MP Camera and camcorder (can be disabled), Barcode Reader
 - Location (GPS, triangulation)
 - 4" Glove-friendly touchscreen
 - Push-to-Talk (PTT)
 - Android OS
- ## Potential Users
- Remote and Mobile Workers
 - Lone Workers
 - Plant Workers
 - Emergency Responders
 - High-Risk Workers



Specifications

	Model XP7 IS (Intrinsically Safe)	Model XP7
CORE PLATFORM/FUNCTIONS		
Operating System	Android 4.4 Kit Kat®	Android 4.4 Kit Kat®
Chipset	MSM8926 1.2 GHz Quad core	MSM8926 1.2 GHz Quad core
Band	LTE B1/B2/B3/B4/B5/B7/B17UMTS 850/900/1900/2100 MHz GSM 850/900/1800/1900 MHz	FDD-LTE B2/B4/B5/B7 B1/B8/B12/ B17UMTS 850/900/1900/2100 MHz GSM 850/900/1800/1900 MHz
Antenna	MISO antenna for LTE	MIMO antenna for LTE
Wi-Fi	802.11 a/b/g/n with hotspot	802.11 a/b/g/n with hotspot
Memory	16 GB eMMC Internal storage/1 GB LPDDR User memory: 12 GB	16 GB Internal storage/1 GB RAM User memory: 12 GB
Applications	Google Play, Push-to-Talk	Google Play, Push-to-Talk
CONNECTIVITY		
Bluetooth, SMS, MMS (text, image, audio, video)	BT 4.0/BLE (Bluetooth Low Energy) Supports SMS and MMS	BT 4.0/BLE (Bluetooth Low Energy) Supports SMS and MMS
GPS, NFC	GPS, GLONASS, A-GPS, NFC	GPS, GLONASS, NFC
Languages supported	English, Spanish	English, French, Chinese, Japanese, Korean
Email Client	EAS, Gmail, POP3, IMAP	EAS, Gmail, POP3, IMAP
BATTERY		
Capacity	Embedded 3600 mAh	Embedded 4800 mAh
Battery Life	Standby: 700 h; Talk: 30 h	Standby: 1000 h; Talk: 40 h
PHYSICAL CHARACTERISTICS		
Size	137 mm x 72.1 mm x 26.9 mm (5.39" x 2.54" x 1.05")	137 mm x 72.1 mm x 20.8 mm (5.39" x 2.54" x 0.82")
Weight	370 g (13 oz)	290 g (10.2 oz)
IP Rating	IP-68	IP-68
Certification and Wireless Approvals	FCC, FCC Chapter 717, IC, PTCRB, GCF, CEC(BSC), IEEE 1725, NFC, Bluetooth SIG, Wi-Fi, CTS, WHQL, IECEX, NEC500 CSA IS Class I, II, III Div 1, Groups A-G T4 ATEX II 2GD Ex ib IIC T4 Gb, Ex ib IIIC T135°C Db	FCC, PTCRB, IEEE1725, CEC, Bluetooth SIG, WFA, IC
Dedicated Keys	PTT key, Alarm key, Power key	PTT key, Alarm key, Power key
Ports	3.5 mm audio connector/magnetic USB connector/12-pin connector	3.5 mm audio connector/magnetic USB connector/12-pin connector
DISPLAY		
Size	4.0"	4.0"
Type	Corning® Gorilla® Glass with glove touch, Blanview display	Corning® Gorilla® Glass with glove touch, Blanview display
Resolution	WVGA (480 x 800)	WVGA (480 x 800)
Outdoor	Yes	Yes
Visibility	16.7 million colors	16.7 million colors
AUDIO		
Microphone	Dual mic solution with noise cancellation	Dual mic solution with noise cancellation
Speaker	19 mm loudspeaker with Gore® protective vents, output up to 103dB	19 mm loudspeaker with Gore® protective vents, output up to 103dB
MULTIMEDIA		
Audio Formats	mp3, WMA 9, AAC, ACC+, eAAC+, AMR-NB/WB	mp3, WMA 9, AAC, ACC+, eAAC+, AMR-NB/WB
Video Formats	Supports avi, mp4, 3GPP	Supports avi, mp4, 3GPP
Media Player	Android native + GMS	Android native + GMS
FM Radio	Yes	Yes
Cameras	8 MP auto-focus rear, 1 MP fixed-focus front	8 MP auto-focus rear, 1 MP fixed-focus front
LED Torch Light	Yes	Yes
ACCESSORIES		
Inbox Accessories	Wall charger Magnetic USB cable with Safety Box Multi-tool	Wall charger Magnetic USB cable with Safety Box Multi-tool

Honeywell Gas Detection

Honeywell is able to provide gas detection solutions to meet the requirements of all applications and industries. Contact us in the following ways:

Headquarters

Europe, Middle East, Africa

Life Safety Distribution GmbH

Javastrasse 2

8604 Hegnau

Switzerland

Tel: +41 (0)44 943 4300

Fax: +41 (0)44 943 4398

gasdetection@honeywell.com

Customer Service:

Tel: 00800 333 222 44 (Freephone number)

Tel: +41 44 943 4380 (Alternative number)

Fax: 00800 333 222 55

Middle East Tel: +971 4 450 5800 (Fixed Gas Detection)

Middle East Tel: +971 4 450 5852 (Portable Gas Detection)

Asia Pacific

Honeywell Analytics Asia Pacific

7F SangAm IT Tower,

434, Worldcupbuk-ro, Mapo-gu,

Seoul 03922

Korea

Tel: +82 (0) 2 6909 0300

Fax: +82 (0) 2 2025 0328

India Tel: +91 124 4752700

China Tel: +86 10 5885 8788 3000

analytics.ap@honeywell.com

Americas

RAE Systems by Honeywell

3775 North First Street

San Jose, CA 95134

USA

Tel: +1 877 723 2878

Honeywell Analytics Distribution Inc.

405 Barclay Blvd.

Lincolnshire, IL 60069

USA

Tel: +1 847 955 8200

Toll free: +1 800 538 0363

Fax: +1 847 955 8210

detectgas@honeywell.com



For more information

www.honeywellanalytics.com

www.raesystems.com

www.honeywell.com

While every effort has been made to ensure accuracy in this publication, no responsibility can be accepted for errors or omissions. Data may change, as well as legislation, and you are strongly advised to obtain copies of the most recently issued regulations, standards, and guidelines. This publication is not intended to form the basis of a contract.

DS1161 | Rev 01 | 02/16
© 2016 Honeywell International Inc.

Honeywell